

Lyric™ Keypad



Optimized for the Honeywell Lyric Controller and Lyric Gateway, the Lyric Keypad enables easy, on-premises security system control for the ultimate convenience and flexibility. Sleek and stylish, it blends with any décor and can be mounted on the wall or placed on tabletops, nightstands or virtually anywhere in the home.

FEATURES

Easier to Install

The small size makes the Lyric Keypad ideal for mounting in tight, hard-to-fit spaces. Installation is simple with the wall mount or optional desk mount kit.

Easier to Sell

Your customers can quickly arm and disarm their systems from any location within the home—a great option that adds value to any sale.

Users can conveniently listen to system status and see updates at a glance.



Lyric™ Keypad

FEATURES AND SPECIFICATIONS

SIZE AND WEIGHT

Height

4.65-inches (118-mm)

Width

3.70-inches (94-mm)

Depth

0.95-inches (25-mm)

Weight

0.55-pounds (0.26-kilograms)

DISPLAY

- Two-line Liquid Crystal Display
 - Up to 16 characters on each line
-

EXTERNAL BUTTONS AND I/O CONNECTORS

Buttons

- Security
- Emergency response

Input and Output

- Speaker

Connectors and Modules

- Backup battery module
-

WIRELESS AND CELLULAR

Antennas

- SiX™ Technology antenna to support Lyric wireless sensors
-

SOUNDS AND VOICE

Sounds

Chime alerts users to sensor status (example: a door opens)

Voice Announcement

Announces system status in English (example: armed away)

EMERGENCY RESPONSE AND ALERTS

Emergency Response

Dedicated emergency response button for users to request assistance from authorities

Emergency Response Types

- Fire
- Police
- Medical

Emergency Alerts*

A loud alarm or sound for:

- Break-ins, when system is armed
 - Potentially unsafe levels of smoke or carbon monoxide
-

Lyric™ Keypad

SETUP AND PROGRAMMING

Remote Programming

- Support for 100% programming and testing using AlarmNet 360™ from a smartphone, tablet, or web browser
- Support for scheduling and delivering software or firmware updates to Lyric keypads over-the-air
- Support for remote diagnostics and troubleshooting

Local Programming

- Support for enrolling keypads into the system at the site in the absence of connection to AlarmNet 360 (for select controls)
- Support for testing installation at the site in the absence of connection to AlarmNet 360 (for select controls)

POWER AND OPERATING CONDITIONS

Power

- Plug-in power supply
- 110VAC to 9VDC/1.0A Adapter

Backup Battery

- 24-hour (600 mAh)
- Rechargeable NiMH cells rated at 7.2VDC

Operating Conditions

32°F-122°F (0°C-50°C)

ORDERING

LKP500-EN	Lyric Keypad
LKP500-ENC	Lyric Keypad (Canada)
LKP500-DK	Lyric Keypad Desk Stand
LKP500-24B	Backup Battery for Lyric Keypad (24-hour)

For more information:

www.honeywell.com/security

Honeywell Security and Fire

2 Corporate Center Dr. Suite 100

P.O. Box 9040

Melville, NY 11747

1.800.323.4576

www.honeywell.com

L/LRCSRTKD/D | 11/2016
© 2016 Honeywell International Inc.

Honeywell